

# WISI OM 10 0648

Transmodulator 6x DVB-S/S2 - 8x QAM/COFDM + 4 CI



## Description

The OM 10 0648 is a micro headend which can transmodulate 6 DVB-S/S2 transponders into 8 DVB-C (QAM) or 8 DVB-T (COFDM) channels.. As it comes with 4 CI slots, it is perfectly suited for the central decryption of pay-tv services. There is also the possibility to create a multiplex before the CI slots allowing the user to combine services from different transponders but to decrypt them by only one smartcard, hereby guaranteeing the efficient usage of professional CAMs. Additionally the OM 10 supports the deletion of unwanted services from a transponder and enables the reduction of output channels by using the output multiplex functionality. External video content can be fed in over USB as a transport stream.

## At a glance:

- Transmodulator of 6 DVB-S/S2 transponders to 8 DVB-C or DVB-T channels
- The integrated 4 in 6 switch matrix reduces the installation effort and DiSEqC 1.0 is increasing the flexibility by controlling up to 4 satellites
- 4 CI slots for central decryption
- PID remapping allows setting of static service PIDs at the output. It is no longer necessary for the TVset to make a scan if there is any transponder modification at the input (Q1 / 17)
- LCN / NIT processing
- Multiplex functionality at the input and output
- USB - interface to feed in any video content (Q1 / 17)
- Programming via web interface
- Integrated DHCP server enables an automatic connection to a PC
- Smartphone and tablet access via Bluetooth

## Technical data

<b>Input</b>	
Impedance	75 Ω
Input frequency range	950...2150 MHz
Input frequency steps	1 MHz
Input level range	50...90 dBμV
Modulation DVB-S	QPSK
Symbol rate DVB-S	1...53 MSps
Modulation DVB-S2	QPSK, 8PSK (EN 302 307), 16APSK, 32 APSK
Symbol rate DVB-S2	1...53 MSps (QPSK); 1...45 MSps (8PSK); 1...35 MSps (16APSK); 1...28 MSps (32APSK)

### CI Processing

Number of PCMCIA slots	4
------------------------	---

### TS Processing

TS stuffing	Yes
SI-Table handling	Yes
NIT handling	Yes
PID remapping	Yes

### QAM Processing

Constellations	64-, 256- QAM
Symbol rate	4,45...7,20 MSymb/s
MER	>40 dB

### COFDM Processing

Constellations	QPSK, 16-, 64-QAM
FEC	1/2, 2/3, 3/4, 5/6, 7/8
Guard Interval	1/8, 1/16, 1/32
FFT Mode	2k, 8k
MER	>40 dB

### Output

Impedance	75 Ω
Output frequency range	110...862 MHz (COFDM); 50...862 MHz (QAM)
Output frequency steps	1 MHz
Output level	90...105 dBμV
Number of channels	8 pcs.
Channel allocation	adjacent (2 blocks per 4 channels)
Return loss	≥14 dB (45 MHz), 1,5 dB/Octave but >10 dB
Output attenuation	0...15 dB (1 dB step)

### Connectors

F-socket	5 pcs. (4x Input, 1x Output)
RJ45	1 pcs.
USB	1 pcs.
Power	DC connector

### General data

Supply voltage	110...240 V (50/60 Hz)
Dimensions (width x height x depth)	272 x 196 x 75 mm
Power consumption	Typ. <40 W (Max. 50 W with 4 LNBS)
Operating temperature range	5...45 °C

## Packaging data

Sales unit	1 pcs.
Dimensions (WxHxD) sales unit	340 x 285 x 175 mm
Packaging volume sales unit	dm³
Gross weight sales unit	2,6 kg
Shipping unit	1 pcs.
Dimensions (WxHxD) shipping unit	mm
Packaging volume shipping package	dm³
Gross weight shipping unit	kg
EAN	4010056747022
Article number	74702
Customs tariff number	85437090